

## ■ DISASSEMBLY PROCEDURE (分解手順)

### Precautions (注意事項)



<ul style="list-style-type: none"> <li>* Disassembly or assembly should be performed on a cloth so as not to damage the LCD.</li> <li>* Install the filament tape and the harness clamp in the same way as they were before removal.</li> <li>* MAC (Media Access Control) address is stored in the DM circuit board. If the DM circuit board is replaced, MAC address will be changed.</li> <li>* Notes on Flat Cable Contacts are visible from the back. Pay attention not to insert and install the cable to the connector inversely. (Photo 1)</li> </ul>	<ul style="list-style-type: none"> <li>※ 液晶ディスプレイを傷つけないために、布の上に置いて作業してください。</li> <li>※ フィラメントテープ、束線止めは、取り外す前と同じように取り付けてください。</li> <li>※ DM シートには、MAC (Media Access Control) アドレスが設定されています。DM シートを交換すると、MAC アドレスが変更されます。</li> <li>※ フラットケーブルの注意 接点が裏面から透けて見えます。コネクタにケーブルの表・裏を逆に差し込まないように注意して取り付けてください。(写真 1)</li> </ul>
 <p>Front Side (表面)</p>	 <p>Back Side (裏面)</p>

Photo 1 (写真 1)

### 1. Lower Case Assembly

(Time required: About 8 minutes)

- 1-1. Remove the twenty-eight (28) screws marked [100]. The two bottom boards can then be removed. (Fig. 1)
- 1-2. Remove the eight (8) screws marked [110], five (5) screws marked [120], two (2) screws marked [130A] and two (2) screws marked [130B]. The lower case assembly can then be removed. (Fig. 1)

### 2. HP Circuit Board

(Time required: About 8 minutes)

- 2-1. Remove the lower case assembly. (See procedure 1.)
- 2-2. Remove the three (3) screws marked [140A]. The HP circuit board can then be removed. (Fig. 2)

### 3. Wheel Assembly, PB Circuit Board

(Time required: About 8 minutes)

- 3-1. Remove the lower case assembly. (See procedure 1.)
- 3-2. Remove the two (2) screws marked [570A]. The PB circuit board can then be removed with the wheel assembly. (Fig. 2)
- \* The wheel assembly is not part of the PB circuit board. When replacing the PB circuit board, remove the wheel assembly from the PB circuit board, and install it on the new circuit board.

### 1. 下ケース Ass'y (所要時間: 約 8 分)

- 1-1. [100] のネジ 28 本を外し、底板 2 枚を外します。(図 1)
- 1-2. [110] のネジ 8 本と [120] のネジ 5 本と [130A] のネジ 2 本と [130B] のネジ 2 本を外し、下ケース Ass'y を外します。(図 1)


### 2. HP シート (所要時間: 約 8 分)

- 2-1. 下ケース Ass'y を外します。(1 項参照)
- 2-2. [140A] のネジ 3 本を外し、HP シートを外します。(図 2)


### 3. ホイール Ass'y、PB シート (所要時間: 約 8 分)

- 3-1. 下ケース Ass'y を外します。(1 項参照)
- 3-2. [570A] のネジ 2 本を外し、ホイール Ass'y と共に PB シートを外します。(図 2)
- ※ ホイール Ass'y は、PB シートの構成部品ではありません。PB シートを交換する際には、PB シートからホイール Ass'y を取り外して、新しいシートに取り付けてください。

<Bottom view (底面図)>



<Top view (上面図)>



※ This figure shows the PSR-S900. (※この図は、PSR-S900 です。)

- [100]: Bind Head Tapping Screw-B (Bタイト+BIND) 4.0X16 MFZN2W3 (WF154100)
- [110]: Bind Head Tapping Screw-B (Bタイト+BIND) 3.0X12 MFZN2W3 (WE987400)
- [120]: Bind Head Tapping Screw-B (Bタイト+BIND) 3.0X16 MFZN2W3 (WE973400)
- [130]: Bind Head Tapping Screw-B (Bタイト+BIND) 3.0X30 MFZN2W3 (WF491000)

Fig. 1 (図1)

#### 4. Wheel, MOD Circuit Board (Time required: About 8 minutes)

- 4-1. Remove the lower case assembly. (See procedure 1.)
- 4-2. Remove the two (2) screws marked [570B]. The MOD circuit board can then be removed with the wheel. (Fig. 2)

\* The wheel is not part of the MOD circuit board. When replacing the MOD circuit board, remove the wheel from the MOD circuit board, and install it on the new circuit board.

#### 4. ホイール、MOD シート (所要時間: 約 8 分)


- 4-1. 下ケース Ass'y を外します。(1 項参照)
- 4-2. [570B] のネジ 2 本を外し、ホイールと共に MOD シートを外します。(図 2)

※ ホイールは、MOD シートの構成部品ではありません。MOD シートを交換する際には、MOD シートからホイールを取り外して、新しいシートに取り付けてください。

#### ● Upper Case Assembly (上ケース Ass'y)

〈Bottom view (底面図)〉

※ This figure shows the PSR-S900.  
(※この図は、PSR-S900 です。)



[140]: Bind Head Tapping Screw-B (Bタイト+BIND) 3.0X8 MFZN2W3 (WE774300)  
 [160A]: PW Head Tapping Screw-B (Bタイト+PWH) 3.0X12 MFZN2W3 (WF002100)  
 [570]: Bind Head Tapping Screw-B (Bタイト+BIND) 3.0X8 MFZN2W3 (WE774300)

Fig. 2 (図2)

#### 5. SW Circuit Board

(Time required: About 8 minutes)

- 5-1. Remove the lower case assembly. (See procedure 1.)
- 5-2. Remove the two (2) screws marked [140B]. The SW circuit board can then be removed. (Fig. 2)

\* The push knob is not part of the SW circuit board. When replacing the SW circuit board, remove the push knob from the SW circuit board, and install it on the new circuit board. (Photo 2)

#### 5. SW シート (所要時間: 約 8 分)

- 5-1. 下ケース Ass'y を外します。(1 項参照)
- 5-2. [140B] のネジ 2 本を外し、SW シートを外します。(図 2)

※ プッシュツマミは、SW シートの構成部品ではありません。SW シートを交換する際には、SW シートからプッシュツマミを取り外して、新しいシートに取り付けてください。(写真 2)




Photo 2(写真2)




Fig. 3(図3)




Fig. 4(図4)

## 6. VR Circuit Board

(Time required: About 9 minutes)

- 6-1. Tie a string or the like to the volume knob. Then, pull the string to remove the volume knob from the control panel side. (Fig. 1, Fig. 3)
- 6-2. Remove the lower case assembly. (See procedure 1.)
- 6-3. Remove the three (3) screws marked [570C]. The VR circuit board can then be removed. (Fig. 2)

## 7. LANL Circuit Board (PSR-S700), LANH Circuit Board (PSR-S900)

(Time required: About 8 minutes)

- 7-1. Remove the lower case assembly. (See procedure 1.)
- 7-2. PSR-S700: Remove the three (3) screws marked [140C]. The LANL circuit board can then be removed. (Fig. 2)
- PSR-S900: Remove the three (3) screws marked [140C]. The LANH circuit board can then be removed. (Fig. 2)

## 8. INV Circuit Board

(Time required: About 8 minutes)

- 8-1. Remove the lower case assembly. (See procedure 1.)
- 8-2. Remove the four (4) screws marked [570D]. The INV circuit board can then be removed. (Fig. 2)

## 9. ENC Circuit Board

(Time required: About 9 minutes)

- 9-1. Tie a string or the like to the encoder knob. Then, pull the string to remove the encoder knob from the control panel side. (Fig. 1, Fig. 4)
- 9-2. Remove the lower case assembly. (See procedure 1.)
- 9-3. Remove the four (4) screws marked [570E]. The ENC circuit board can then be removed. (Fig. 2)

## 6. VR シート (所要時間: 約 9 分)

- 6-1. コントロールパネル面より、V ツマミを、紐状のものでひっかけるようにして外します。(図1、図3)
- 6-2. 下ケース Ass'y を外します。(1 項参照)
- 6-3. [570C] のネジ 3 本を外し、VR シートを外します。(図 2)

## 7. LANL シート (PSR-S700)、LANH シート (PSR-S900) (所要時間: 約 8 分)

- 7-1. 下ケース Ass'y を外します。(1 項参照)
- 7-2. PSR-S700: [140C] のネジ 3 本を外し、LANL シートを外します。(図 2)
- PSR-S900: [140C] のネジ 3 本を外し、LANH シートを外します。(図 2)

## 8. INV シート (所要時間: 約 8 分)

- 8-1. 下ケース Ass'y を外します。(1 項参照)
- 8-2. [570D] のネジ 4 本を外し、INV シートを外します。(図 2)

## 9. ENC シート (所要時間: 約 9 分)

- 9-1. コントロールパネル面より、エンコーダツマミを、紐状のものでひっかけるようにして外します。(図1、図4)
- 9-2. 下ケース Ass'y を外します。(1 項参照)
- 9-3. [570E] のネジ 4 本を外し、ENC シートを外します。(図 2)

## 10. Shield Cover U, Shield Cover L, DM Circuit Board

10-1. Remove the lower case assembly. (See procedure 1.)

### 10-2. Shield Cover L (PSR-S700) (Time required: About 8 minutes)

10-2-1. Remove the three (3) screws marked [140D] and the screw marked [160A]. The shield cover L can then be removed. (Fig. 2)

### 10-3. Shield Cover L (PSR-S900) (Time required: About 8 minutes)

10-2-1. Remove the four (4) screws marked [140E]. The shield cover L can then be removed. (Fig. 2)

### 10-4. DM Circuit Board (PSR-S700) (Time required: About 9 minutes)

10-4-1. Remove the shield cover L. (See procedure 10-2.)

10-4-2. Remove the four (4) screws marked [140F]. The DM circuit board can then be removed. (Fig. 5)

\* **MAC (Media Access Control) address is stored in the DM circuit board. If the DM circuit board is replaced, the MAC address will be changed. (Photo 3)**

\* **The DM circuit board has a built-in jumper switch for switching the display in Japanese or in English (SW3). (Photo 4)**

### 10-5. DM Circuit Board (PSR-S900) (Time required: About 10 minutes)

10-5-1. Remove the shield cover L. (See procedure 10-3.)

10-5-2. Remove the eight (8) screws marked [140G]. The DM circuit board can then be removed. (Fig. 5)

\* **MAC (Media Access Control) address is stored in the DM circuit board. If the DM circuit board is replaced, the MAC address will be changed. (Photo 3)**

\* **The DM circuit board has a built-in jumper switch for switching the display in Japanese or in English (SW1). (Photo 4)**

### 10-6. Shield Cover U (Time required: About 9 minutes)

10-6-1. Remove the shield cover L.  
(PSR-S700: See procedure 10-2.)  
(PSR-S900: See procedure 10-3.)

10-6-2. Remove the two (2) screws marked [140H]. The shield cover U can then be removed with the DM circuit board. (Fig. 5)

10-6-3. Remove the DM circuit board from the shield cover U.  
(PSR-S700: See procedure 10-4-2.)  
(PSR-S900: See procedure 10-5-2.)

## 10. シールドカバー上、シールドカバー下、DM シート

10-1. 下ケース Ass'y を外します。(1 項参照)

### 10-2. シールドカバー下 (PSR-S700) (所要時間: 約 8 分)

10-2-1. [140D] のネジ 3 本と [160] のネジ 1 本を外し、シールドカバー下を外します。(図 2)

### 10-3. シールドカバー下 (PSR-S900) (所要時間: 約 8 分)

10-3-1. [140E] のネジ 4 本を外し、シールドカバー下を外します。(図 2)

### 10-4. DM シート (PSR-S700) (所要時間: 約 9 分)

10-4-1. シールドカバー下を外します。(10-2 項参照)

10-4-2. [140F] のネジ 4 本を外し、DM シートを外します。(図 5)

※ DM シートには、MAC (Media Access Control) アドレスが設定されています。DM シートを交換すると、MAC アドレスが変更されます。(写真 3)

※ DM シート内には、日本語と英語の表示切替え用 (SW3) のジャンパー SW があります。(写真 4)

### 10-5. DM シート (PSR-S900) (所要時間: 約 10 分)

10-5-1. シールドカバー下を外します。(10-3 項参照)

10-5-2. [140G] のネジ 8 本を外し、DM シートを外します。(図 5)

※ DM シートには、MAC (Media Access Control) アドレスが設定されています。DM シートを交換すると、MAC アドレスが変更されます。(写真 3)

※ DM シート内には、日本語と英語の表示切替え用 (SW1) のジャンパー SW があります。(写真 4)

### 10-6. シールドカバー上 (所要時間: 約 9 分)

10-6-1. シールドカバー下を外します。

(PSR-S700: 10-2 項参照)

(PSR-S900: 10-3 項参照)

10-6-2. [140H] のネジ 2 本を外し、DM シートと共にシールドカバー上を外します。(図 5)

10-6-3. シールドカバー上から DM シートを外します。

(PSR-S700: 10-4-2 項参照)


(PSR-S900: 10-5-2 項参照)



● Upper Case Assembly (上ケース Ass'y)

＜Bottom view (底面図)＞

※ This figure shows the PSR-S900. (※この図は、PSR-S900 です。)



[130C]: Bind Head Tapping Screw-B (Bタイト+BIND) 3.0X30 MFZN2W3 (WF491000)  
 [140]: Bind Head Tapping Screw-B (Bタイト+BIND) 3.0X8 MFZN2W3 (WE774300)  
 [160B]: PW Head Tapping Screw-B (Bタイト+PWH) 3.0X12 MFZN2W3 (WF002100)

Fig. 5 (図5)

● Jumper switch (ジャンパー SW)

● PSR-S900



MAC address (MAC アドレス)

Photo 3 (写真3)

● PSR-S700





Photo 4 (写真4)

**11. DJK Circuit Board****(Time required: About 10 minutes)**

- 11-1. Remove the lower case assembly. (See procedure 1.)
- 11-2. Remove the shield cover L.  
(PSR-S700: See procedure 10-2.)  
(PSR-S900: See procedure 10-3.)
- 11-3. Remove the shield cover U with the DM circuit board. (See procedure 10-6.)
- 11-4. Remove the four (4) screws marked [140I], the screw marked [160B] and the screw marked [140J]. The DJK circuit board can then be removed. (Fig. 5)

**12. EIF Circuit Board****(Time required: About 9 minutes)**

- 12-1. Remove the lower case assembly. (See procedure 1.)
- 12-2. Remove the shield cover L.  
(PSR-S700: See procedure 10-2.)  
(PSR-S900: See procedure 10-3.)
- 12-3. Remove the shield cover U with the DM circuit board. (See procedure 10-6.)
- 12-4. Remove the four (4) screws marked [570F]. The EIF circuit board can then be removed. (Fig. 6)

**13. Keyboard Assembly****(Time required: About 8 minutes)**

- 13-1. Remove the lower case assembly. (See procedure 1.)
- 13-2. Remove the screw marked [130C]. The keyboard assembly can then be removed. (Fig. 5)

**11. DJK シート (所要時間: 約 10 分)**

- 11-1. 下ケース Ass'y を外します。(1 項参照)
- 11-2. シールドカバー下を外します。  
(PSR-S700: 10-2 項参照)  
(PSR-S900: 10-3 項参照)
- 11-3. DM シートと共にシールドカバー上を外します。  
(10-6 項参照)
- 11-4. [140I] のネジ 4 本と [160B] のネジ 1 本、[140J] のネジ 1 本を外し、DJK シートを外します。(図 5)

**12. EIF シート (所要時間: 約 9 分)**


- 12-1. 下ケース Ass'y を外します。(1 項参照)
- 12-2. シールドカバー下を外します。  
(PSR-S700: 10-2 項参照)  
(PSR-S900: 10-3 項参照)
- 12-3. DM シートと共にシールドカバー上を外します。  
(10-6 項参照)
- 12-4. [570F] のネジ 4 本を外し、EIF シートを外します。  
(図 6)

**13. 16M 鍵盤 EMKSA (所要時間: 約 8 分)**

- 13-1. 下ケース Ass'y を外します。(1 項参照)
- 13-2. [130C] のネジ 1 本を外し、16M 鍵盤 EMKSA を外します。(図 5)

**● Upper Case Assembly (上ケース Ass'y)****< Bottom view (底面図) >**

※ This figure shows the PSR-S900. (※この図は、PSR-S900 です。)



[160C]: PW Head Tapping Screw-B (Bタイト+PWH) 3.0X12 MFZN2W3 (WF002100)

[570]: Bind Head Tapping Screw-B (Bタイト+BIND) 3.0X8 MFZN2W3 (WE774300)

Fig. 6 (図6)

**14. PNL Circuit Board****(Time required: About 11 minutes)**

- 14-1. Remove the lower case assembly. (See procedure 1.)
- 14-2. Remove the shield cover L.  
(PSR-S700: See procedure 10-2.)  
(PSR-S900: See procedure 10-3.)
- 14-3. Remove the shield cover U with the DM circuit board. (See procedure 10-6.)
- 14-4. Remove the keyboard assembly. (See procedure 13.)
- 14-5. Remove the screw marked [160C]. The ferrite core and DM holder S can then be removed. (Fig. 6)
- 14-6. Remove the fourteen (14) screws marked [570H]. The PNL circuit board can then be removed. (Fig. 6)

**15. PNR Circuit Board****(Time required: About 11 minutes)**

- 15-1. Remove the lower case assembly. (See procedure 1.)
- 15-2. Remove the keyboard assembly. (See procedure 13.)
- 15-3. Remove the fifteen (15) screws marked [570I]. The PNR circuit board can then be removed. (Fig. 6)

**16. PNCA Circuit Board, PNCB Circuit Board, LCD**

- 16-1. Remove the lower case assembly. (See procedure 1.)
- 16-2. Remove the shield cover L.  
(PSR-S700: See procedure 10-2.)  
(PSR-S900: See procedure 10-3.)
- 16-3. Remove the shield cover U with the DM circuit board. (See procedure 10-6.)

**16-4. PNCA Circuit Board****(Time required: About 13 minutes)**

- 16-4-1. PSR-S700: Remove the LANL circuit board.  
(See procedure 7.)  
PSR-S900: Remove the LANH circuit board.  
(See procedure 7.)
- 16-4-2. Remove the DJK circuit board. (See procedure 11.)
- 16-4-3. Remove the two (2) screws marked [570J] and two (2) screws marked [570K]. The LCD holder can then be removed. (Fig. 6)
- 16-4-4. Turn up the shield sheet (A) and remove the thirteen (13) screws marked [570L]. The PNCA circuit board can then be removed. (Fig. 6)

**16-5. PNCB Circuit Board****(Time required: About 10 minutes)**

- 16-5-1. Remove the keyboard assembly. (See procedure 13.)
- 16-5-2. Remove the eight (8) screws marked [570M]. The PNCB circuit board can then be removed. (Fig. 6)

**16-6. LCD (Time required: About 10 minutes)**

- 16-6-1. Remove the DJK circuit board. (See procedure 11.)
- 16-6-2. Turn up the shield sheet (A) and remove the two (2) screws marked [570J] and two (2) screws marked [570N]. The LCD can then be removed. (Fig. 6)

**14. PNL シート (所要時間: 約 11 分)**

- 14-1. 下ケース Ass'y を外します。(1 項参照)
- 14-2. シールドカバー下を外します。  
(PSR-S700: 10-2 項参照)  
(PSR-S900: 10-3 項参照)
- 14-3. DM シートと共にシールドカバー上を外します。  
(10-6 項参照)
- 14-4. 16M 鍵盤 EMKSA を外します。(13 項参照)
- 14-5. [160C] のネジ 1 本を外し、フェライトコアと DM 固定金具 (小) を外します。(図 6)
- 14-6. [570H] のネジ 14 本を外し、PNL シートを外します。(図 6)

**15. PNR シート (所要時間: 約 11 分)**

- 15-1. 下ケース Ass'y を外します。(1 項参照)
- 15-2. 16M 鍵盤 EMKSA を外します。(13 項参照)
- 15-3. [570I] のネジ 15 本を外し、PNR シートを外します。  
(図 6)

**16. PNCA シート、PNCB シート、液晶ディスプレイ**

- 16-1. 下ケース Ass'y を外します。(1 項参照)
- 16-2. シールドカバー下を外します。  
(PSR-S700: 10-2 項参照)  
(PSR-S900: 10-3 項参照)
- 16-3. DM シートと共にシールドカバー上を外します。  
(10-6 項参照)

**16-4. PNCA シート (所要時間: 約 13 分)**

- 16-4-1. PSR-S700: LANL シートを外します。(7 項参照)  
PSR-S900: LANH シートを外します。(7 項参照)
- 16-4-2. DJK シートを外します。(11 項参照)
- 16-4-3. [570J] のネジ 2 本と [570K] のネジ 2 本を外し、LCD 固定金具を外します。(図 6)
- 16-4-4. シールドシート (A) をめくって [570L] のネジ 13 本を外し、PNCA シートを外します。(図 6)

**16-5. PNCB シート (所要時間: 約 10 分)**

- 16-5-1. 16M 鍵盤 EMKSA を外します。(13 項参照)
- 16-5-2. [570M] のネジ 8 本を外し、PNCB シートを外します。(図 6)

**16-6. 液晶ディスプレイ (所要時間: 約 10 分)**

- 16-6-1. DJK シートを外します。(11 項参照)
- 16-6-2. シールドシート (A) をめくって [570J] のネジ 2 本と [570N] のネジ 2 本を外し、液晶ディスプレイを外します。(図 6)



**17. Tweeter (PSR-S700)****(Time required: About 8 minutes)**

- 17-1. Remove the lower case assembly. (See procedure 1.)
- 17-2. Remove the two (2) screws marked [140K]. The tweeter can then be removed. (Fig. 2)
- \* **The left and right tweeters can be removed in the same method.**

**18. Tweeter (PSR-S900)****(Time required: About 8 minutes)**

- 18-1. Remove the lower case assembly. (See procedure 1.)
- 18-2. Remove the two (2) screws marked [140L]. The tweeter can then be removed. (Fig. 2)
- \* **The left and right tweeters can be removed in the same method.**

**19. Woofer (PSR-S700)****(Time required: About 8 minutes)**

- 19-1. Remove the lower case assembly. (See procedure 1.)
- 19-2. Remove the four (4) screws marked [60A]. The woofer can then be removed. (Fig. 7)
- \* **The left and right woofers can be removed in the same method.**

**20. Woofer (PSR-S900)****(Time required: About 8 minutes)**

- 20-1. Remove the lower case assembly. (See procedure 1.)
- 20-2. Remove the four (4) screws marked [60B]. The woofer and four (4) speaker holders can then be removed. (Fig. 7)
- \* **The left and right woofers can be removed in the same method.**

**21. Speaker Grille Assembly (L)****(Time required: About 10 minutes)**

- 21-1. Remove the lower case assembly. (See procedure 1.)
- 21-2. Remove the INV circuit board. (See procedure 8.)
- 21-3. Restraighten the eight (8) projections marked [A] to come off the slots of the upper case assembly. (Fig. 6)
- 21-4. Remove the speaker grille assembly (L). (Fig. 1)

**22. Speaker Grille Assembly (R)****(Time required: About 11 minutes)**

- 22-1. Remove the lower case assembly. (See procedure 1.)
- 22-2. Remove the shield cover L.  
(PSR-S700: See procedure 10-2.)  
(PSR-S900: See procedure 10-3.)
- 22-3. Remove the shield cover U with the DM circuit board. (See procedure 10-6.)
- 22-4. Remove the EIF circuit board. (See procedure 12.)
- 22-5. Restraighten the eight (8) projections marked [B] to come off the slots of the upper case assembly. (Fig. 6)
- 22-6. Remove the Speaker Grille assembly (R). (Fig. 1)

**17. ツィーター (PSR-S700) (所要時間: 約 8 分)**

- 17-1. 下ケース Ass'y を外します。(1 項参照)
- 17-2. [140K] のネジ 2 本を外し、ツィーターを外します。(図 2)
- ※ 左右のツィーターは、それぞれ同じ方法で外すことができます。

**18. ツィーター (PSR-S900) (所要時間: 約 8 分)**

- 18-1. 下ケース Ass'y を外します。(1 項参照)
- 18-2. [140L] のネジ 2 本を外し、ツィーターを外します。(図 2)
- ※ 左右のツィーターは、それぞれ同じ方法で外すことができます。

**19. ウーファー (PSR-S700) (所要時間: 約 8 分)**

- 19-1. 下ケース Ass'y を外します。(1 項参照)
- 19-2. [60A] のネジ 4 本を外し、ウーファーを外します。(図 7)
- ※ 左右のウーファーは、それぞれ同じ方法で外すことができます。

**20. ウーファー (PSR-S900) (所要時間: 約 8 分)**

- 20-1. 下ケース Ass'y を外します。(1 項参照)
- 20-2. [60B] のネジ 4 本を外し、ウーファーとウーファー固定金具 4 個を外します。(図 7)
- ※ 左右のウーファーは、それぞれ同じ方法で外すことができます。

**21. SP グリル Ass'y (L) (所要時間: 約 10 分)**


- 21-1. 下ケース Ass'y を外します。(1 項参照)
- 21-2. INV シートを外します。(8 項参照)
- 21-3. [A] の 8 箇所のフックを上ケース Ass'y の溝と平行にします。(図 6)
- 21-4. SP グリル Ass'y (L) を外します。(図 1)

**22. SP グリル Ass'y (R) (所要時間: 約 11 分)**

- 22-1. 下ケース Ass'y を外します。(1 項参照)
- 22-2. シールドカバー下を外します。  
(PSR-S700: 10-2 項参照)  
(PSR-S900: 10-3 項参照)
- 22-3. DM シートと共にシールドカバー上を外します。(10-6 項参照)
- 22-4. EIF シートを外します。(12 項参照)
- 22-5. [B] の 8 箇所のフックを上ケース Ass'y の溝と平行にします。(図 6)
- 22-6. SP グリル Ass'y (R) を外します。(図 1)


● Lower Case Assembly (下ケース Ass'y)

〈Rear view (背面図)〉



〈Top view (上面図)〉

※ This figure shows the PSR-S900. (※この図は、PSR-S900 です。)



[60]: Bind Head Tapping Screw-B (Bタイト+BIND) 4.0X8 MFZN2W3 (WE974600)  
 [90]: Bind Head Tapping Screw-B (Bタイト+BIND) 3.0X8 MFZN2W3 (WE774300)

Fig. 7(図7)

23. AM Circuit Board  
 (Time required: About 9 minutes)

- 22-1. Remove the lower case assembly. (See procedure 1.)
- 22-2. Remove the eight (8) screws marked [90A] and two (2) screws marked [90B]. The AM circuit board can then be removed. (Fig. 7)

23. AM シート (所要時間: 約 9 分)

- 23-1. 下ケース Ass'y を外します。(1 項参照)
- 23-2. [90A] のネジ 8 本と [90B] のネジ 2 本を外し、AM シートを外します。(図 7)